

README for DigiPoster-III Firmware Update

Firmware Version: 1.10.1.37677
Date: 21.09.2012

This firmware update file is intended to update the DigiPoster-III firmware.

Name of firmware update file:
`setup_DigiPoster-III_Firmware_PA-24-XXX_v1.10.1_V1.bin`

It can be installed on board configuration:
- PA-24-xxx

It can be installed on firmware versions:
- 1.2.0
- 1.4.0
- 1.6.0
- 1.8.0
- 1.10.0

ATTENTION:

The power supply for DigiPoster-III must NOT be interrupted during the firmware installation because this can damage the product!

The DigiPoster-III automatically restarts during the firmware installation. This is normal behaviour.

The firmware update procedure takes about 5 minutes.

Preparations for the firmware update:

Download the firmware zip file "DigiPoster-III_Firmware_PA-24-XXX_v1.10.1_V1.zip" from our homepage (see <http://www.datadisplay-group.com/support/downloads/mediaplayer-firmware/>) and save it on your computer.

Extract the contained firmware file and install this on your DigiPoster-III as described below.

The firmware can be installed by using one of the following methods:

- Upload per web interface:

- Open the web interface of DigiPoster-III
- Select the menu "Advanced"
- Browse the firmware update file in the section "Firmware Update" and press the button "Upload to DigiPoster-III"
- Wait about 5 minutes and consider the messages in your browser until the installation has finished

- Upload per USB flash drive:

- Copy the firmware update file into the root directory of an USB flash drive
- Insert the USB flash drive into the USB port of your DigiPoster-III
- Wait about 5 minutes until the installation has finished

- Upload per ACC 3:

- Open the Windows software ACC version 3.18 or above
- Select menu "Settings -> Upload setup file"
- Browse the firmware update file by pressing the button "Open setup"
- Select the device you want to update (must be setup as connection before)
- Press the button "Start" to upload the firmware update file
- Wait about 5 minutes and consider the messages in the log window until the installation has finished

- Download from FTP server:

- Configure the DigiPoster-III to poll playlists from a FTP server (this can be done in the web interface in menu "Content Auto Update")
- Create a folder "setup" in the playlist directory on the FTP server
- Upload the firmware update file to this directory by using ACC 3 or a standard FTP client (e.g. FileZilla)
- When next polling interval of DigiPoster-III occurs, it downloads the firmware update file and installs it automatically

Data Display Group
Augsburger Str. 2b
D-82110 Germering
Germany
